


Instructions to Install and Run Bluetooth on PC

1. Installation


1. Insert CD and copy across the self-extracting archive file v51012T_20070531.exe to the desktop.
2. Run the file from the desktop, the following window will show:



3. Press 'Next'. The following window will then show:




4. Select 'I accept' then press 'Next'. The following window will show:




5. Press 'Install' and wait.


6. When prompted, insert the bluetooth adapter into the USB port and press 'OK'.



7. Press 'Finish' when prompted with the following:




8. The PC must be rebooted before the Bluetooth adapter can be used.




2. To run the Bluetooth adapter with a Tag

1. Place a magnet against the glass reed-switch near the +ve battery terminal. A green LED on a small PCB near the back of the tag should flash periodically.




2. Run the bluetooth manager (icon located in start-up list in bottom right corner of the screen).




3. Press 'New Connection', the following window appears:




4. Press 'Next', the following window appears when the bluetooth adapter is located:




5. Press 'Next', the following window will appear:




6. Note the number of the COM port selected (COM 40 in this case) and press 'Next'. The following window will appear:



7. Double click on the SMRU Icon, the window should change to the following:



8. Run the file TagConfig.exe from the CD, the following window will open:




9. Enter the COM port from earlier, in the above example this is entered as 40. (Top-right of screen)


10. The TagConfig application should now be running, indicating tag time etc and the LED on the Bluetooth adapter should show a red LED rather than a flashing green one. **Note:** It may be necessary to select another com port in the TagConfig application and then re-selecting the required port in order for the TagConfig application to register the change.
11. FLASH data may be downloaded by pressing the 'Save to File' button. Once saved the data in FLASH should be deleted in order to prevent the memory from completely filling.

3. To Close Down an Established Link

1. Close TagConfig application and remove magnet.
2. Disconnect the Bluetooth link as shown below:



3. Press 'Yes' when prompted at the following:



4. Press the 'Delete' button to remove the link (Note: this needs to be deleted as it won't work with the other tag – it is necessary to follow the whole of Section 2 to interface to the other tag).
5. When prompted with the following, press 'Yes'.



6. Close the application